

ENTRACOMP® 28SA Plus

Smart Access Control Unit



The ENTRACOMP® 28SA Plus is a highly sophisticated, yet simple to use, card access control unit for single or multidoor applications. Simply place the card on the stainless steel TOUCH CARD® Reader plate, and the card is read instantly and accurately. Patented slotless TOUCH CARD® Reader technology protects the unit from weather and vandalism.

The unit may be programmed with a PC either locally or with the use of a modem. Basic programming functions can also be accomplished by using programming cards. Transaction information is stored by the unit and may be downloaded to a PC or printer. Up to 128 28SA Plus units can be connected together in a single twisted pair RS-485 network using optional SK-NM485 Modules and SK-NET™ Software for Windows® 95/ 98/NT/2000.

A remote reader (SK-029W) may be connected to the ENTRACOMP® 28SA Plus to allow access control in both directions through a single passageway, including true IN/OUT anti-passback capability. Three inputs are provided which are user programmable as Door Monitor, Tamper Monitor, Remote Inactive, Remote Open, Arming Circuit, Bell, or User Defined. The limited use feature allows cards to be programmed to work for a specified number of uses, days, weeks, or days after the first use.



- 65,500 Card Capacity
- 5,000 Stored Transactions
- 15 Time Zones / 32 Holidays
- Connect up to 128 Units with Optional SK-NM485 Module and SK-NET™ Software
- Audit Trail Upload to PC or Connect to Serial Printer
- Modem Capability for Remote Locations
- TCP/IP Capability for LAN Connection
- Weather Resistant for Outdoor Installation
- True IN/OUT or Timed Antipassback





Specifications subject to change without notice


© COPYRIGHT 2002 5515



All dimensions in drawings are indicated in inches.







PHYSICAL	Width 4.00" (10 Height 4.60" (11 Weight 17 oz. (0.	72 cm) 1.50" (3.81 cm) 1.75" (4.45 cm) .16 cm) 5.50" (13.97cm) 4.00" (10.16 cm) .68 cm) 7.63" (19.38 cm) 5.80" (14.73 cm)
POWER REQUIREMENTS	Without Remote Reader With Remote Reader (SK-029W)	12-24 VAC or DC, 125 mA 12-16 VAC or DC, 250 mA
OUTPUTS	Latch & Alarm Shunt Tamper (optional)	DPDT contact, 3A, up to 277 VAC or 30 VDC SPDT contact, 115 VAC, 2A maximum
INPUTS	Auxiliary 1 (Door Monitor)* Auxiliary 2 (Disabled)* Auxiliary 3 (Disabled)* *Factory Default - can be char	Requires SPST contact closure Requires SPST contact closure Requires SPST contact closure aged via PC.
COMMUNICATION	RS-232 (5-Wire Shielded Cable) RS-485 (Single Twisted Pair) Remote Reader Modem LAN Printer	Serial RS-232. Up to 38.4K baud, full duplex, (8N1) Requires Optional SK-NM485 Network Module. See Separate Data Sheet for specifications. 31 bit or 26 bit Wiegand type input 10-21 VDC @ 150 mA supplied to remote reader, depending on input voltage supplied to 28SA <i>Plus</i> Requires Hayes compatible - 1.2 to 38.4k baud Requires external device server Serial Printer (or Parallel printer with serial converter)
ENVIRONMENT	Ambient Temperature Humidity	-40° F to 158° F (-40° C to 70° C) 0% to 95% relative humidity (non-condensing)
OPERATIONAL	Memory Card Capacity Limited Use Cards Transaction Storage Time Zones Facility Code Latch/Alarm Shunt Timer Antipassback Auxiliary Inputs (3)	Non-volatile 65,500 4,000 programmable from 1-500 uses, days, weeks 5,000 events 15 for card access, 1 door unlock time zone; full week plus holiday in one-half hour segments; 32 programmable holidays; selectable automatic daylight saving time. Up to 3 different codes simultaneously. (Max. # of cards 65,500) Programmable from 1/4 to 30 seconds Real or Timed (1 to 30 minutes); hard or soft Programmable for door monitor, tamper monitor, remote

This product complies with UL 294 Standards, CE (European Standards), and with Part 15 of Class B FCC Rules.

WARRANTY (U.S. and Canadian)

"This product is warranted against defects in materials and workmanship for a period of 2 years from the date of purchase. Secura Key shall, at its option, either replace or repair this product, if returned to us freight prepaid within the warranty period. This warranty does not include freight, taxes, duties, or installation expenses. THE WARRANTY SET FORTH ABOVE IS EXCLUSIVE AND NO OTHER WARRANTY, WHETHER WRITTEN OR ORAL, IS EXPRESSED OR IMPLIED. SECURA KEY SPECIFICALLY DISCLAIMS ANY IMPLIED WARRANTIES OR MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. The remedies provided herein are the buyers' sole and exclusive remedies. In no event shall Secura Key be liable for direct, indirect, special, incidental or consequential damages (including loss of profits), whether based on contract, tort or any other legal theory." Contact Secura Key for Card/Tag and Export Warranty Policies.

DISTRIBUTED BY:



open, remote inactive, bell, arming circuit or user defined

20301 NORDHOFF STREET
CHATSWORTH, CA 91311
PHONE (818) 882-0020 • FAX (818) 882-7052
TOLL FREE (800) 891-0020
E-mail: mail@securakey.com
Web site: www.securakey.com