

ADEMCO VISTA-10P

Control Panel



Honeywell's VISTA-10P is a six-zone control panel designed to address security dealers' most important needs. It significantly reduces dealer training and service call costs thanks to user-friendly features that make operation easier than ever, and offers increased upsell opportunities through its expansion capabilities and flexibility.

The feature-rich panel is the industry's most economical control and is ideally suited for a wide range of applications.

FEATURES

- | | | |
|---|---|---|
| <ul style="list-style-type: none"> • Six hardwired zones on board • 16 wireless expansion zones totaling 22 protection zones • Eight independent keyfob zones allow two wireless keys to be programmed without using any of the 22 zones • 32 Event log • 16 user codes • One configurable zone type allows installers to create their own custom zone type • Two on-board triggers • Four output devices using a 4204 relay module • Programmable to meet SIA false alarm prevention specifications. To meet UL approval for ANSI/SIA CP-01-2000 order part number VISTA-20PSIA | <p>Valuable End-User Features</p> <ul style="list-style-type: none"> • Flexible function keys allow single button arming • One programmable macro key • Viewable on system keypad display <ul style="list-style-type: none"> – Exit countdown – Time and date* – Event log* • Two schedules <ul style="list-style-type: none"> – Can activate relays on programmed times or on events – Latchkey reports to a pager – “User Access” time windows | <ul style="list-style-type: none"> • Chime by zone • 4286 Phone Module allows system control from any touchtone phone • Four output devices with multiple actions per device <ul style="list-style-type: none"> – Turn lights on when system disarms with a 4204 relay – Flash same lights when system is in alarm using a 4204 relay |
|---|---|---|

ADEMCO VISTA-10P

Control Panel

SPECIFICATIONS

Electrical

- Aux power 12VDC, 600mA max
- Seven hour standby at 400 mA aux load with four amp hour battery
- 16.5VAC/25VA transformer
- Alarm output 12VDC, 2.0 amps max
- For UL installations, combined aux and alarm output cannot exceed 700mA

Output Control

- Supports multiple output devices, one 4204 and two triggers

Zones

- Six hardwired zones
- Selectable response: 10msec, 350msec, 750msec
- 16 selectable zone types plus one configurable zone type
- Programmable swinger suppression

Expansion Devices

- 4204 - Up to four relays - 15mA standby (each active relay draws an additional 40mA)

Accessories

- 4286 VIP Voice Module – 220mA
- 5881ENL supports up to eight zones – 60mA, 5881ENM supports up to 16 zones – 50mA, 5883 Transceiver supports up to 16 zones – 80mA
- Supports Eagle 1225 and 1221 boards

Keypads

- 6160 Custom Alpha (required for programming) – 100mA
- 6160V Custom Alpha Voice – 100mA
- 6150 Fixed English LCD - 85mA/40mA
- 6150V Fixed English Voice LCD – 85mA/40mA
- 6150RF Fixed English RF LCD - 85mA/40mA
- 6148 Fixed English LCD – 70mA/30mA

Agency Listings

- UL Residential Fire, Burglary and CSFM

Smoke Detectors

- Supports four-wire smoke detectors

Communications

- Touchtone or pulse
- Formats supported
 - ADEMCO Contact ID
 - ADEMCO 4 + 2 Express
 - ADEMCO low speed
 - Sescoa/Radionics
- 3 + 1, 4 + 1 and 4 + 2 reporting
- Reporting capabilities
 - Split
 - Dual
 - Split/Dual - True dial tone detection
- Low battery reports 11.2 – 11.6VDC
- AC loss and restoral reporting supported

ORDERING

VISTA-10P	Control Panel
V10PACKP	Preboxed Kit

Honeywell Security & Custom Electronics

165 Eileen Way, Syosset, NY 11791
www.ademco.com